

MMS-32H



### Manual Motor Starters

Code	Frame Size	Rating AC3		Thermal Adjustable Range (A)	Dimensions		
		kW Rating	Amps		W	H	D
MMS-32H/00.16A	MMS-32H	0.08	0.13	0.1 - 0.16	45	94	86
MMS-32H/00.25A		0.13	0.25	0.16 - 0.25			
MMS-32H/00.4A		0.18	0.4	0.25 - 0.4			
MMS-32H/00.63A		0.2	0.63	0.4 - 0.63			
MMS-32H/01.0A		0.3	1	0.63 - 1.0			
MMS-32H/01.6A		0.55	1.6	1.0 - 1.6			
MMS-32H/02.5A		0.75	2.5	1.6 - 2.5			
MMS-32H/04A		1.5	4	2.5 - 4.0			
MMS-32H/06A		2.2	6	4 - 6			
MMS-32H/08A		3	8	5 - 8			
MMS-32H/10A		4	10	6 - 10			
MMS-32H/13A		5.5	13	9 - 13			
MMS-32H/17A		7.5	17	11 - 17			
MMS-32H/22A		10	22	14 - 22			
MMS-32H/26A		11	26	18 - 26			
MMS-32H/32A	15	32	22 - 32				
MMS-63S/40A	MMS-63S	18.5	40	28 - 40	55	140	130
MMS-63S/450A		22	50	34 - 50			
MMS-63S/63A		30	63	45 - 63			
MMS-100S/075A	MMS-100S	37	75	55 - 75	70	165	157
MMS-100S/090A		45	90	70 - 90			
MMS-100S/100A		55	100	80 - 100			

### Auxiliary Contacts

Code	Type	Description	Applicable	Contacts
FX2A	FX	Front Mount	MMS-32 - MMS-100	2NO
FX1A1B				1NO + 1NC
FX2B				2NC
LX2A	LX	Side Mount	MMS-32 - MMS-100	2NO
LX1A1B				1NO + 1NC
LX2B				2NC



LX-11



FX-11